

S486

CMOS IC

DUAL 100mW AUDIO POWER AMPLIFIER WITH STANDBY MODE

■ DESCRIPTION

The UTC **S486** is a dual power amplifier capable of delivering typically 100mW per channel of continuous average power to an 8Ω load with 0.1% THD+N using a 5V power supply.

The UTC **S486** features an externally controlled, low-power consumption stand by mode. The UTC **S486** exhibit a low quiescent current of typically 1.8mA, allowing usage in portable applications.


The unity-gain stable UTC **S486** can be configured by external gain-setting resistors.

■ FEATURES


- * Operating voltage range $V_{CC}=2V \sim 5.5V$
- * Output power:
 - 102mW @5V into 16Ω with 0.1% THD+N max (1kHz)
- * Stand by mode available
- * Low current consumption: 2.5mA max
- * Click and pop reduction circuitry
- * Unity-gain stable
- * Short circuit protected

■ ORDERING INFORMATION


Ordering Number		Package	Packing
Lead Free	Halogen Free		
S486L-S08-R	S486G-S08-R	SOP-8	Tape Reel
S486L-SM1-R	S486G-SM1-R	MSOP-8	Tape Reel



■ MARKING



■ PIN CONFIGURATION



■ ABSOLUTE MAXIMUM RATING ($T_A=25^\circ\text{C}$)

PARAMETER		SYMBOL	RATINGS	UNIT
Supply voltage (Note 2)		V_{CC}	6	V
Input Voltage		V_{IN}	$-0.3V \sim V_{CC}+0.3V$	V
Output Short Circuit to V_{CC} or GND			Continuous(Note 3)	
Power Dissipation ($T_J=150^\circ\text{C}$)	SOP-8	P_D	0.71	W
	MSOP-8		0.58	W
Junction Temperature		T_J	+150	$^\circ\text{C}$
Operating Temperature		T_{OPR}	-40 ~ +85	$^\circ\text{C}$
Storage Temperature		T_{STG}	-65 ~ +150	$^\circ\text{C}$

Notes: 1. Absolute maximum ratings are those values beyond which the device could be permanently damaged.

Absolute maximum ratings are stress ratings only and functional device operation is not implied.

2. All voltage values are measured with respect to the ground pin.

3. Attention must be paid to continuous power dissipation ($V_{DD} \times 300\text{mA}$). Exposure of the I_C to a short circuit for an extended time period is dramatically reducing product life expectancy.

■ THERMAL DATA

PARAMETER		SYMBOL	RATINGS	UNIT
Junction to Ambient	SOP-8	θ_{JA}	175	$^\circ\text{C}/\text{W}$
	MSOP-8		215	$^\circ\text{C}/\text{W}$

■ RECOMMENDED OPERATING CONDITIONS

PARAMETER		SYMBOL	RATINGS	UNIT
Supply Voltage		V_{CC}	2 ~ 5.5	V
Standby Voltage Input	ACTIVE	V_{STB}	$1.5 \leq V_{STB} \leq V_{CC}$	V
	STANDBY		$GND \leq V_{STB} \leq 0.4$ (Note)	V
Load Resistor		R_L	≥ 16	Ω
Load Capacitor	$R_L = 16 \sim 100\Omega$	C_L	400	pF
	$R_L > 100\Omega$		100	pF
Junction to Ambient		θ_{JA}	150	$^\circ\text{C}/\text{W}$

Note: The minimum current consumption (I_{STB}) is guaranteed at GND for the whole temperature range.

■ ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$, GND = 0V, unless otherwise specified)For $V_{CC} = +5\text{V}$

PARAMETER	SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Output Swing	V_{OUT}	$V_{OL}: R_L=32\Omega$			0.45	0.5	V
		$V_{OH}: R_L=32\Omega$		4.45	4.52		
		$V_{OL}: R_L=16\Omega$			0.6	0.7	
		$V_{OH}: R_L=16\Omega$		4.2	4.35		
Input Offset Voltage	$V_{I(OFF)}$	$V_{ICM}=V_{CC}/2$			1		mV
Supply Current	I_{CC}	No input signal, no load			1.8	2.5	mA
Stand By Current	I_{STB}	No input signal, $V_{STB}=\text{GND}$, $R_L=32\Omega$			10	1000	nA
Input Bias Current	$I_{I(BIAS)}$	$V_{ICM}=V_{CC}/2$			90	200	nA
Max Output Current	I_{OUT}	$\text{THD}+N \leq 1\%$, $R_L=16\Omega$ connected between out and $V_{CC}/2$		106	115		mA
Output Power	P_{OUT}	$\text{THD}+N=0.1\% \text{ Max}, F=1\text{kHz}$		$R_L=16\Omega$	102		mW
				$R_L=32\Omega$	64		
		$\text{THD}+N=1\% \text{ Max}, F=1\text{kHz}$		$R_L=16\Omega$	95	108	
				$R_L=32\Omega$	60	65	
Total Harmonic Distortion + Noise ($G_V=-1$)	THD+N	$R_L=32\Omega, P_{OUT}=60\text{mW}, 20\text{Hz} \leq F \leq 20\text{kHz}$			0.3		%
		$R_L=16\Omega, P_{OUT}=90\text{mW}, 20\text{Hz} \leq F \leq 20\text{kHz}$			0.3		
Power Supply Rejection Ratio	PSRR	Inputs grounded ($G_V=-1$) (Note), $R_L \geq 16\Omega$, $C_B=1\text{mF}$, $F=1\text{kHz}$, $V_{RIPPLE}=200\text{mV}_{PP}$		53	58		dB
Signal-to-Noise Ratio	SNR	(A weighted, $G_V=-1$) (Note), $R_L=32\Omega$, $\text{THD}+N < 0.4\%$, $20\text{Hz} \leq F \leq 20\text{kHz}$		80	103		dB
Crosstalk	CT	Channel Separation, $G_V=-1$, $F=1\text{kHz}$		$R_L=16\Omega$	80		dB
				$R_L=32\Omega$	83		
		Channel Separation, $G_V=-1$, $F=20\text{Hz} \sim 20\text{kHz}$		$R_L=16\Omega$	72		
				$R_L=32\Omega$	79		
Input Capacitance	C_{IN}				1		pF
Gain Bandwidth Product	GB_W	$R_L=32\Omega$			1.1		MHz
Slew Rate	SR	Unity Gain Inverting ($R_L=16\Omega$)			0.4		V/ μ s

Note: Guaranteed by design and evaluation.

■ ELECTRICAL CHARACTERISTICS(Cont.) ($T_A = 25^\circ\text{C}$, GND = 0V, unless otherwise specified)For $V_{CC} = +3.3\text{V}$

PARAMETER	SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Output Swing	V_{OUT}	$V_{OL}: R_L=32\Omega$			0.3	0.38	V
		$V_{OH}: R_L=32\Omega$		2.85	3		
		$V_{OL}: R_L=16\Omega$			0.45	0.52	
		$V_{OH}: R_L=16\Omega$		2.68	2.85		
Input Offset Voltage	$V_{I(OFF)}$	$V_{ICM}=V_{CC}/2$			1		mV
Supply Current	I_{CC}	No inputsignal, noload			1.8	2.5	mA
Stand By Current	I_{STB}	No inputsignal, $V_{STB}=\text{GND}$, $R_L=32\Omega$			10	1000	nA
Input Bias Current	$I_{I(BIAS)}$	$V_{ICM}=V_{CC}/2$			90	200	nA
Max Output Current	I_{OUT}	THD+N≤1%, $R_L=16\Omega$ connectedbetweenoutand $V_{CC}/2$		64	75		mA
Output Power	P_{OUT}	THD+N=0.1% Max, $F=1\text{kHz}$		$R_L=16\Omega$	38		mW
				$R_L=32\Omega$	26		
		THD+N=1% Max, $F=1\text{kHz}$		$R_L=16\Omega$	36	42	
				$R_L=32\Omega$	23	28	
Total Harmonic Distortion + Noise ($G_V=-1$)	THD+N	$R_L=32\Omega$, $P_{OUT}=60\text{mW}$, $20\text{Hz}\leq F\leq 20\text{kHz}$			0.3		%
		$R_L=16\Omega$, $P_{OUT}=90\text{mW}$, $20\text{Hz}\leq F\leq 20\text{kHz}$			0.3		
Power Supply Rejection Ratio	PSRR	inputsgrounded($G_V=-1$)(Note2), $R_L \geq 16\Omega$, $C_B=1\text{mF}$, $F=1\text{kHz}$, $V_{RIPPLE}=200\text{mV}_{PP}$		53	58		dB
Signal-to-Noise Ratio	SNR	(Aweighted, $G_V=-1$)(Note2), $R_L=32\Omega$, THD+N<0.4%, $20\text{Hz}\leq F\leq 20\text{kHz}$		80	98		dB
Crosstalk	CT	ChannelSeparation, $G_V=-1$, $F=1\text{kHz}$		$R_L=16\Omega$	77		dB
				$R_L=32\Omega$	80		
		ChannelSeparation, $G_V=-1$, $F=20\text{Hz}\sim 20\text{kHz}$		$R_L=16\Omega$	69		
				$R_L=32\Omega$	76		
Input Capacitance	C_{IN}				1		pF
Gain Bandwidth Product	GBw	$R_L=32\Omega$			1.1		MHz
Slew Rate	SR	UnityGainInverting ($R_L=16\Omega$)			0.4		V/ μ s

Note 1. All electrical values are guaranteed with correlation measurements at 2V and 5V.

2. Guaranteed by design and evaluation.

■ ELECTRICAL CHARACTERISTICS(Cont.) ($T_A = 25^\circ\text{C}$, GND = 0V, unless otherwise specified)For $V_{CC} = +2.5\text{V}$

PARAMETER	SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Output Swing	V_{OUT}	$V_{OL}: R_L=32\Omega$			0.25	0.32	V
		$V_{OH}: R_L=32\Omega$		2.14	2.25		
		$V_{OL}: R_L=16\Omega$			0.35	0.45	
		$V_{OH}: R_L=16\Omega$		1.97	2.15		
Input Offset Voltage	$V_{I(OFF)}$	$V_{ICM}=V_{CC}/2$			1		mV
Supply Current	I_{CC}	No inputsignal, noload			1.7	2.5	mA
Stand By Current	I_{STB}	No inputsignal, $V_{STB}=\text{GND}$, $R_L=32\Omega$			10	1000	nA
Input Bias Current	$I_{I(BIAS)}$	$V_{ICM}=V_{CC}/2$			90	200	nA
Max Output Current	I_{OUT}	THD+N≤1%, $R_L=16\Omega$ connectedbetweenoutand $V_{CC}/2$		45	56		mA
Output Power	P_{OUT}	THD+N=0.1% Max, F=1kHz		$R_L=16\Omega$	21		mW
				$R_L=32\Omega$	13		
		THD+N=1% Max, F=1kHz		$R_L=16\Omega$	17.5	22	
				$R_L=32\Omega$	12.5	14	
Total Harmonic Distortion + Noise ($G_V=-1$)	THD+N	$R_L=32\Omega$, $P_{OUT}=60\text{mW}$, $20\text{Hz}\leq F\leq 20\text{kHz}$			0.3		%
		$R_L=16\Omega$, $P_{OUT}=90\text{mW}$, $20\text{Hz}\leq F\leq 20\text{kHz}$			0.3		
Power Supply Rejection Ratio	PSRR	inputsgrounded($G_V=-1$)(Note2), $R_L \geq 16\Omega$, $C_B=1\text{mF}$, F=1kHz, $V_{RIPPLE}=200\text{mV}_{PP}$		53	58		dB
Signal-to-Noise Ratio	SNR	(Aweighted, $A_V=-1$)(Note2), $R_L=32\Omega$, THD+N<0.4%, $20\text{Hz}\leq F\leq 20\text{kHz}$		80	95		dB
Crosstalk	CT	ChannelSeparation, $G_V=-1$, F=1kHz		$R_L=16\Omega$	77		dB
				$R_L=32\Omega$	80		
		ChannelSeparation, $G_V=-1$, F=20Hz~20kHz		$R_L=16\Omega$	69		
				$R_L=32\Omega$	76		
Input Capacitance	C_{IN}				1		pF
Gain Bandwidth Product	GBP	$R_L=32\Omega$			1.1		MHz
Slew Rate	SR	UnityGainInverting ($R_L=16\Omega$)			0.4		V/ μ s

Note 1. All electrical values are guaranteed with correlation measurements at 2V and 5V.


2. Guaranteed by design and evaluation.

■ ELECTRICAL CHARACTERIST(Cont.) ($T_A = 25^\circ\text{C}$, GND = 0V, unless otherwise specified)For $V_{CC} = +2\text{V}$

PARAMETER	SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Output Swing	V_{OUT}	$V_{OL}:R_L=32\Omega$			0.24	0.29	V
		$V_{OH}:R_L=32\Omega$		1.67	1.73		
		$V_{OL}:R_L=16\Omega$			0.33	0.41	
		$V_{OH}:R_L=16\Omega$		1.53	1.63		
Input Offset Voltage	$V_{I(OFF)}$	$V_{ICM}=V_{CC}/2$			1		mV
Supply Current	I_{CC}	No inputsignal, noload			1.7	2.5	mA
Stand By Current	I_{STB}	No inputsignal, $V_{STB}=\text{GND}$, $R_L=32\Omega$			10	1000	nA
Input Bias Current	$I_{I(BIAS)}$	$V_{ICM}=V_{CC}/2$			90	200	nA
Max Output Current	I_{OUT}	$\text{THD}+N \leq 1\%$, $R_L=16\Omega$ connectedbetweenoutand $V_{CC}/2$		33	41		mA
Output Power	P_{OUT}	$\text{THD}+N=0.1\% \text{ Max}, F=1\text{kHz}$		$R_L=16\Omega$	12		mW
				$R_L=32\Omega$	8		
		$\text{THD}+N=1\% \text{ Max}, F=1\text{kHz}$		$R_L=16\Omega$	9.5	13	
				$R_L=32\Omega$	7	9	
Total Harmonic Distortion + Noise ($G_V=-1$)	$\text{THD}+N$	$R_L=32\Omega, P_{OUT}=60\text{mW}, 20\text{Hz} \leq F \leq 20\text{kHz}$			0.3		%
		$R_L=16\Omega, P_{OUT}=90\text{mW}, 20\text{Hz} \leq F \leq 20\text{kHz}$			0.3		
Power Supply Rejection Ratio	PSRR	inputsgrounded ($G_V=-1$)(Note), $R_L \geq 16\Omega$, $C_B=1\text{mF}$, $F=1\text{kHz}$, $V_{RIPPLE}=200\text{mV}_{PP}$		52	57		dB
Signal-to-Noise Ratio	SNR	(Aweighted, $G_V=-1$)(Note), $R_L=32\Omega$, $\text{THD}+N < 0.4\%$, $20\text{Hz} \leq F \leq 20\text{kHz}$		80	93		dB
Crosstalk	CT	ChannelSeparation, $G_V=-1$, $F=1\text{kHz}$		$R_L=16\Omega$	77		dB
				$R_L=32\Omega$	80		
		ChannelSeparation, $G_V=-1$, $F=20\text{Hz} \sim 20\text{kHz}$		$R_L=16\Omega$	69		
				$R_L=32\Omega$	76		
Input Capacitance	C_{IN}				1		pF
Gain Bandwidth Product	GBP	$R_L=32\Omega$			1.1		MHz
Slew Rate	SR	UnityGainInverting ($R_L=16\Omega$)			0.4		V/ μ s

Note: Guaranteed by design and evaluation.







■ TYPICAL APPLICATION CIRCUIT









COMPONENTS INFORMATION

Components	Functional Description
$R_{IN1, 2}$	Inverting input resistor which sets the closed loop gain in conjunction with R_{FEED} . This resistor also forms a high pass filter with C_{IN} ($f_c = 1 / (2 \pi R_{IN} \times C_{IN})$).
$C_{IN1, 2}$	Input coupling capacitor which blocks the DC voltage at the amplifier's input terminal.
$R_{FEED1, 2}$	Feedback resistor which sets the closed loop gain in conjunction with R_{IN} . $A_v = \text{Closed Loop Gain} = -R_{FEED}/R_{IN}$.
C_S	Supply Bypass capacitor which provides power supply filtering.
C_B	Bypass capacitor which provides half supply filtering.
$C_{OUT1, 2}$	Output coupling capacitor which blocks the DC voltage at the load input terminal. This capacitor also forms a high pass filter with R_L ($f_c = 1 / (2 \pi R_L \times C_{OUT})$).






■ TYPICAL CHARACTERISTICS



■ TYPICAL CHARACTERISTICS(Cont.)



■ TYPICAL CHARACTERISTICS(Cont.)



UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice.

